#### TEST PROCEDURE FOR HASSELBLAD FIELD IRRADIANCE

(NASA-CR-141776) TEST PROCEDURE FOR HASSELBLAD FIELD IRRADIANCE (Lockheed Electronics Co.) 20 p HC \$3.25 CSCL 14E

N75-22685

Unclas G3/35 19471

Prepared By

Lockheed Electronics Company, Inc

Aerospace Systems Division

Houston, Texas

Contract NAS-9-12200

For

CAMERA AND OPTICAL ENGINEERING DEPARTMENT

National Aeronautics and Space Administration

LYNDON B. JOHNSON SPACE CENTER

Houston, Texas

April 1975



	RT INDEX/ABSTRACT s on reverse side.)
TEST PROCEDURE FOR HASSELBLAD FIE	LD IRRADIANCE JSC-09629
3. CONTRACTOR/ORGANIZATION NAME	4. CONTRACT OR GRANT NO.
LOCKHEED ELECTRONICS COMPANY	NAS-9-12200
5. CONTRACTOR/ORIGINATOR DOCUMENT NO.	6. PUBLICATION DATE (THIS ISSUE)
LEC-5968	APRIL 1975
7. SECURITY CLASSIFICATION UNCLASSIFIED	FRED PEARCE
T. LIMITATIONS GUVERNMENT HAS UNLIMITED RIGHTS XX YES NO	CONNIE GEORGE
LE NO, STATE LIMITATIONS AND AUTHORITY	
11. DOCUMENT CONTRACT REFERENCES	12. HARDWARE CONFIGURATION
NORK BREAKDOWN STRUCTURE NO. NA	NA NA
CONTRACT EXHIBIT NO.	SUBSYSTEM .
NA OHL NO. AND REVISION	NA MAJOR EQUIPMENT GROUP
NA	NA NA
. NA	
	RE FOR DETERMINING THE UNIFORMITY O IRRADIANCE) OF HASSELBLAD CAMERAS.
14. \$08;	ECT TERMS
_ASTP	
e	
ERAP	

JSC-09629

## PROJECT DOCUMENT COVER SHEET

TEST	PROCEDURE
	FOR
HAS	SELBLAD
FIELD	IRRADIANCE
REPORT NUMBER ED82-AC-662	DATE

PREPARED BY:	C. George	Approved: P. M. Wiffiths
APPROVED:	ED/8 F. Pearce	
APPROVED:	ED/8 H. Kuéhnel	'tA Kuchnel
APPROVED:	(PROGRAM OFFICE) ND/5 D. Dittmar	Mittura 4/15/25

REVISIONS

DATE PREPARED BY

BRANCH

DIVISION

REPORT NUMBER

REPORT NUMBER

## NASA-JSC HOUSTON, TEXAS

PAGE i OF iii

DATE April 1975

## TABLE OF CONTENTS

PARAGRAPH	TITLE	PAGE
1.0	PURPOSE	1
2.0	APPLICATION	1
3.0	TEST EQUIPMENT	. 1
4.0	TEST PROCEDURE	1
4.1	Equipment Setup	1.
4.2	Calibration Procedure	1

NASA-JSC

PAGE'ii OF iii

HOUSTON, TEXAS

DATE April 1975

### LIST OF FIGURES

NO.		•	TIT	<u>LE</u>	PA	.GE
3-1	FIELD	IRRADIANCE	TEST	SETUP		2

NASA-JSC HOUSTON, TEXAS PAGE iii OF iii DATE April 1975

### LIST OF TABLES

NO.	TITLE	PAGE
4 - 1	DATA SHEET FOR FIELD IRRADIANCE	
	PART I- CHECKOUT	5
•	PART II - EQUIPMENT ID/DATA RECORDING	11

HOUSTON, TEXAS

PAGE 1 OF 14

DATE April 1975

#### 1.0 PURPOSE

The purpose of this document is to define the procedure for determining the uniformity of film plane illumination (field irradiance) of the Hasselblad cameras.

The data source shall consist of photographs, with X-Y scans being taken for indication only. The accuracy requirement is 2.0%.

#### 2.0 APPLICATION

This document is applicable to all Hasselblad lens field irradiance tests unless otherwise specified. All data and comments are to be recorded on the Data Sheet, Part II (see Table 4-1). All testing shall be verified by Government inspection.

#### 3.0 TEST EQUIPMENT

The following equipment is utilized in the determination of field irradiance. (See Figure 3-1 for an illustration of the test setup.)

- Photometer, Gamma Model 2020, S/N 793
- Photomultiplier, Gamma Model 2020-1, S/N 784
- Automatic Photometer Scan, NASA No. 86684
- Hasselblad Mounting Fixture
- Beck Hemisphere, S/N 002
- IL700 Research Radiometer, S/N 84
- Variac
- IL700 Detector, PT171C, S/N 86
- Power Source, NASA No. 36129 (DC Power Supply)
- Shutter Release Box
- Fiber Optic Probe with Cosine Adapter (.016" Salisbury cap attached)

#### 4.0 TEST PROCEDURE

- 4.1 Equipment Setup
- 4.1.1 Record test equipment and test article part number (P/N) and/or serial number (S/N) on the Data Sheet, Part II.
- 4.1.2 Verify that test equipment is operational.
- 4.2 <u>Calibration Procedure</u>
- 4.2.1 Mount the camera and lens on the Hasselblad mounting fixture.

TO BE PROVIDED

HOUSTON, TEXAS

PAGE 3 OF 14 DATE April 1975

Verify that the mounting fixture is in correct orientation 4.2.2 (i.e., the bottom thumbscrews shall be all the way up so that the camera is vertical).

- Set Variac to required voltage. Verify with the IL700 4.2.3 photometer. Record data on the Data Sheet.
- 4.2.4 Open the camera shutter.
- Put the X-Y scanner into manual control and check the 4.2.5 X-Y scan plane manually.

THE MAIN DATA SOURCE CONSISTS OF NOTE: PHOTOGRAPHS. THE X-Y SCAN IS FOR INDICATION ONLY.

- With the X-Y scanner in manual control, define the 4.2.6 following:
  - X-start position

  - Increment size of X
    Number of increments in X
  - Y-start position

  - Increment size of Y Number of increments in Y

Record information on Data Sheet, Part I.

- Check for photometer and set it to a range of 100 + 5 4.2.7 by varying the HV adjust.
- Set f/number to the largest aperture. Record on Data 4.2.8 Sheet, Part I.
- Run X-Y scan as per the parameters derived in Paragraph 4.2.9 4.2.6.
- Repeat Step 4.2.6 for the center veritcal scan of film plane. 4.2.10
- Remove fiber probe assembly and install magazine con-4.2.11 taining type 3400 film.
- Turn off scanner and close camera shutter. 4.2.12
- Set the camera to the largest f/number (smallest numerical 4.2.13 setting). Record on Data Sheet, Part I.
- Set exposure time to matrix value for largest f/number 4.2.14 (smallest numerical setting). Record on Data Sheet, Part I.

HOUSTON, TEXAS . .

DATE April 1975

- 4.2.15 Open the camera shutter.
- 4.2.16 Take three data frames and blank two.
- 4.2.17 Set the lens to the next f/number until all f/numbers below f/16 have been completed. Record on Data Sheet, Part I. When all f/numbers below f/16 have been completed, go to Paragraph 4.2.19.
- 4.2.18 Repeat Paragraphs 4.2.14 through 4.2.17.
- 4.2.19 Place the second lens on the camera and repeat Paragraphs 4.2.13 and all following steps. With the second lens on the camera, repeat Paragraphs 4.2.2 through 4.2.10.
- 4.2.20 Turn off all test equipment.
- 4.2.21 Remove Hasselblad camera from calibration setup.

PAGE <u>5 OF 14</u>

DATE <u>April 1975</u>

REPORT ED82-AC-662

HOUSTON, TEXAS

TABLE 4-1
DATA SHEET FOR
FIELD IRRADIANCE
PART I - CHECKOUT

PARA	DESCRIPTION	INSPECTION
ŘĚF		
4.1.1	P/N's and/or S/N's of the test equipment recorded on Part II of the Data Sheet	
4.1.2	Equipment is operational.	
4.2.1	Camera and lens are mounted on the Hasselblad mounting fixture.	
4.2.2	The Hasselblad mounting fixture is in correct orientation (i.e., the camera is vertical).	
4.2.3	The Variac is set to the following voltage and verified with the IL700 photometer	
	•	
4.2.4	The camera shutter is open.	
4.2.5	The X-Y scanner is in manual control.	
	The X-Y scan plane is checked manually.	
4.2.6	The X-Y scanner is in manual control.	
	The following are defined:	
	<ul> <li>X-start position:</li> <li>Increment size of X:</li> <li>Number of increments in X:</li> <li>Y-start position:</li> <li>Increment size of Y:</li> <li>Number of increments in Y:</li> </ul>	
4.2.7	The photometer is checked and set to a range of 100 +5 by varying the HV adjust.	

PAGE	6	_0F_	14	
DATE	Anni	1 10	7.5	

REPORT ED82-AC-662

HOUSTON, TEXAS

TABLE 4-1 (CONT'D)

PART I - CHECKOUT

PARA REF	DESCRIPTION	INSPECTION
4.2.8	The f/number is set to the largest aperture as follows:	
4.2.9	The X-Y scan is run using the parameters defined in Paragraph 4.2.6 of the Data Sheet, Part I.	
4.2.10	Repeat Step 4.2.6 for the center verical scan of film plane.	
4.2.11	The fiber probe assembly is removed.	
	Magazine containing type 3400 file is installed.	
4.2.12	Scanner is turned off.	
	Camera shutter is closed.	
4.2.13	The f/number is set to the largest f/number (smallest numerical setting) as follows:	
·		
4.2.14	Exposure time is set to matrix value for largest f/number (smallest numerical setting) as follows:	
4.2.15	The camera shutter is open.	<i>)</i> -
4.2.16	Three data frames are taken.	
	Two data frames are blanked.	

PAGE 7 OF 14

REPORT ED82-AC-662

HOUSTON, TEXAS

DATE April 1975

TABLE 4-1 -(CONT'D)
PART I - CHECKOUT

PARA REF	DESCRIPTION	INSPECTION
4.2.17	The lens is set to the next f/number until all f/numbers below f/16 are completed. The f/numbers used are as follows:	
:	Upon completing all f/numbers below f/16, the steps in Paragraph 4.2.19 are performed.	
4.2.18	Steps in Paragraph 4.2.14 through 4.2.17 are performed as follows:	
	A. Paragraph 4.2.14. Exposure time is set to matrix value for largest (smallest numerical setting) f/number as follows:	
	B. Paragraph 4.2.15. The camera shutter is open.	
	C. Paragraph 4.2.16. Three data frames are taken. Two data frames are blanked.	
	D. Paragraph 4.2.17. The lens is set to the next f/number until all f/numbers below f/16 are completed. The f/numbers used are as follows:	
	•	

PAGE 8 OF 14

HOUSTON, TEXAS

REPORT ED82-AC-662

DATE April 1975

TABLE 4-1 - (CONT'D)

PART I CHECKOUT

PARA REF	DESCRIPTION	INSPECTION
4.2.19	The second lens is placed on the camera and steps described in Paragraphs 4.2.13 through 4.2.17 are performed.	
	A. Paragraph 4.2.13. The f/number is set to the largest f/number (smallest numerical setting) as follows:	
· · · · ·	B. Paragraph 4.2.14. Exposure time is set to matrix value for largest f/number (smallest numerical setting) as follows:	
	•	
o O	C. Paragraph 4.2.15. The camera shutter is open.	· · ·
-	D. Paragraph 4.2.16. Three data frames are taken.	
	Two data frames are blanked.	• •
	E. Paragraph 4.2.17. The lens is set to the next f/number until all f/numbers below f/16 have been used. The f/numbers used are as follows:	
	• • • •	
· : .	If the second lens is already on the camera, the steps described in Paragraphs 4.2.2 through 4.2.10 are performed as follows:	,

PAGE 9 OF 14

DATE April 1975

REPORT ED82-AC-662

DOUSTON, TEXAS

TABLE 4-1 (CONT'D)

PART I - CHECKOUT

PARA REF	DESCRIPTION	INSPECTION
4.2.19 (Cont d)	1. Paragraph 4.2.2. The Hasselblad mounting fixture is in correct orientation (i.e., the camera is vertical).	
	2. Paragraph 4.2.3. The Variac is set to the following voltage and verified with the IL700 photometer.	
	3. Paragraph 4.2.4. The camera shutter is open	:
	4. Paragraph 4.2.5. The X-Y scanner is in manual control.	
	The X-Y scanner is checked manually.	
	5. Paragraph 4.2.6. The X-Y scanner is in manual control.	
	The following are defined:	
	<ul> <li>X-start position:</li> <li>Increment size of X:</li> <li>Number of increments in X:</li> <li>Y-start position:</li> <li>Increment size of Y:</li> <li>Number of increments in Y:</li> </ul>	
	6. Paragraph 4.2.7. The photometer is checked and set to a range of 100 ±5 by varying the HV adjust.	
	7. Paragraph 4.2.8. The f/number is set to the largest aperture as follows:	

PAGE 10 OF 14

HOUSTON, TEXAS

REPORT ED82-AC-662

DATE April 1975

TABLE 4-1 (CONT'D)

PART I - CHECKOUT

PARA REF	DESCRIPTION	INSPECTION
4.2.19 (Cont'd)	8. Paragraph 4.2.9. The X-Y scan is run using the parameters defined in Paragraph 4.2.6 of the data sheet.	
	9. Paragraph 4,2.10. Repeat Step 4.2.6 for the center vertical scan of film plane.	
4.2.20	All test equipment is turned off.	
4.2.21	Hasselblad camera is removed from calibration setup.	

PARA REF	ADDITIONAL STEPS REQUIRED BY TPS (WHERE APPLICABLE)	INSPECTION	
·			
÷		*	

HOUSTON, TEXAS

DATE April 1975

# TABLE 4-1 (CONT'D) PART II - EQUIPMENT ID/DATA RECORDING

<del>`</del>	TEST	EQUIPMENT	S/N	P/N	TEST ARTICLE	S/N	P/N	
тесн:	Photo Mode	ometer, Gamma 1 2020			***			
	Phot Gamm	omultiplier, a Model 2020-1	,					
		matic Photometer , NASA No. 86684		,				
TEST T	Hass Fixt	elblad Mounting ure						
	Beck	Hemisphere	-	, .				
		O Research ometer						
	Vari	ac						
	1L70 PT17	0 Detector, 1C		,				
ENGINEER	Powe No.	r Source, NASA 36129	·					
RIS	1	ter Release Box	,					
ST	with	r Optic Probe Cosine Adapter attached)						
TE	NO.				ORMATION			
	1.	1L700 CHECK OF I	HEMISPH	ERE				
		• Variac set	at	v	olts		•	
		• IL700		•				
		Function						
DATE:		Suppress						
Α.		Range				· · · · ·		

PAGE 12 OF 14

REPORT ED82-AC-662

HOUSTON, TEXAS

DATE April 1975

TABLE 4-1 (CONT'D)
PART II - EQUIPMENT ID/DATA RECORDING

NO.	ADDITIONAL INFORMATION
1. Cont'd	Sensitivity factor Variac IL700 x 10 <sup>-9</sup>
NO.	REMARKS

HOUSTON, TEXAS

DATE April 1975

# TABLE 4-1 (CONT'D) PART II - EQUIPMENT ID/DATA RECORDING

1	TEST EQUIPMENT	S/N	P/N	TEST ARTICLE	S/N	P/N		
твсн:	Photometer, Gamma Model 2020							
	Photomultiplier, Gamma Model 2020-1							
	Automatic Photometer Scan, NASA No. 86684							
TEST T	Hasselblad Mounting Fixture					. *		
[	Beck Hemisphere			,				
	IL700 Research Radiometer			,				
	Variac		}					
	IL700 Detector, PT171C							
ENGINEER:	Power Source, NASA No. 36129			· · · · · · · · · · · · · · · · · · ·				
GIN	Shutter Release Box							
ST EN	Fiber Optic Probe with Cosine Adapter (cap attached)		-					
TE	• · · · · · · · · · · · · · · · · · · ·	DDITION.	AL INF	ORMATION				
	1. IL700 CHECK OF I	немі sphi	ERE			-		
	• Variac set	at	ν.	olts				
	• 11.700	-						
	Function							
DATE	Suppression							
l a	Range							

PAGE 14 OF 14

REPORT ED82-AC-662

HOUSTON, TEXAS

DATE April 1975

TABLE 4-1 (CONT'D)

PART II - EQUIPMENT ID/DATA RECORDING

	NO.	ADDITIONAL INFORMATION
Co	l. nt'd	Sensitivity factor Variac IL700 x 10 <sup>-9</sup>
		-
	NO.	REMARKS